



CR-DS505

YH1(S),YJ1(S)
YL1(S)

CR-D500

YU(S),YH1(S)
YL1(S),YJ1(S)

SERVICE MANUAL

RADIO RECEIVER

- Replace this Service Manual with "Revision Publishing" when it is issued.

aiwa
S/M Code No. 09-003-343-6T2

SIMPLE
DATA

ELECTRICAL MAIN PARTS LIST - 1

NOTE: The characters in the suffix column indicate the part usage.

DS505YH1(S)XX.....	B.....
DS505YJ1(S)XX.....	C.....
DS505YL1(S)XX.....	D.....
D500YU(S)XX.....	F.....
D500YH1(S)XX.....	H.....
D500YJ1(S)XX.....	I.....
D500YL1(S)XX.....	J.....

REF.NO	PARTS NO.	NO.	DESCRIPTION	SUFFIX
C	405	87-010-183-080	0E C-CAP,S 2700P-50 B	ABCDE.....
C	455	87-010-183-080	0E C-CAP,S 2700P-50 B	ABCDE.....
C	303	87-010-188-080	0E CAP,CHIP 6800P	ABCDE.....
C	103	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	121	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	123	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	125	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	128	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	403	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	407	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	423	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	453	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	457	87-010-196-080	0E CHIP CAPACITOR,0.1-25	ABCDE.....
C	102	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	110	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	112	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	114	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	124	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	130	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	131	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	132	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	420	87-010-197-080	0E CAP, CHIP 0.01 DM	ABCDE.....
C	108	87-010-324-080	0E C-CAP,S 1P-50UJ	ABCDE.....
C	111	87-010-328-080	0E C-CAP,S 5P-50 UJ	ABCDE.....
C	115	87-010-328-080	0E C-CAP,S 5P-50 UJ	ABCDE.....
C	107	87-010-333-080	0E S-CHIP UJ 10P	ABCDE.....
C	117	87-010-334-080	0E C-CAP,S 12P-50 UJ	ABCDE.....
C	105	87-010-341-080	0E C-CAP,S47P-50UJ	ABCDE.....
C	301	87-010-341-080	0E C-CAP,S47P-50UJ	ABCDE.....
C	401	87-010-428-080	0E C-CAP,S 0.015-25 B	ABCDE.....
C	451	87-010-428-080	0E C-CAP,S 0.015-25 B	ABCDE.....
C	133	87-010-568-080	0E C-CAP,S 150P-50 UJ	ABCDE.....
C	101	87-010-570-080	0E C-CAP,S 220P-50 UJ	ABCDE.....
C	118	87-010-572-080	0E C-CAP,S 330P-50 UJ	ABCDE.....
C	116	87-010-573-080	0E C-CAP,S 390P-50 UJ	ABCDE.....
C	104	87-010-574-080	0E C-CAP,S 470P-50 UJ	ABCDE.....
C	109	87-010-575-080	0E C-CAP,S 560P-50 UJ	ABCDE.....
C	120	87-010-805-080	0E CAP, S 1-16	ABCDE.....
C	122	87-010-805-080	0E CAP, S 1-16	ABCDE.....
C	304	87-010-805-080	0E CAP, S 1-16	ABCDE.....
C	126	87-016-526-080	0E C-CAP,S 0.47-16 BK	ABCDE.....
C	402	87-016-526-080	0E C-CAP,S 0.47-16 BK	ABCDE.....
C	452	87-016-526-080	0E C-CAP,S 0.47-16 BK	ABCDE.....
IC	401	87-017-642-080	1D IC,CXA1622M	ABCDE.....
VC	102	87-017-925-070	1A C-VARI CAP,KV1460	ABCDE.....
VC	103	87-017-925-070	1A C-VARI CAP,KV1460	ABCDE.....
Q	104	87-026-467-080	0E TR,HN1C01F (0.3W)	ABCDE.....
IC	101	87-A21-407-040	1E C-IC,TA2104BFN	ABCDE.....
VC	101	87-A40-462-040	1B C-VARI-CAP,SVC347(S)	ABCDE.....
Q	102	89-115-884-080	0E CHIP -TRANSISTER 2SA1588Y	ABCDE.....
Q	301	89-341-165-080	0E CHIP TRANSISTOR 2SC4116GR	ABCDE.....
Q	302	89-341-165-080	0E CHIP TRANSISTOR 2SC4116GR	ABCDE.....
Q	101	89-342-153-080	0E TR,2SC4215	ABCDE.....
Q	103	89-342-153-080	0E TR,2SC4215	ABCDE.....
Q	105	89-342-153-080	0E TR,2SC4215	ABCDE.....
C	405	87-010-183-080	0E C-CAP,S 2700P-50 BFGHIJK
C	455	87-010-183-080	0E C-CAP,S 2700P-50 BFGHIJK
C	303	87-010-188-080	0E CAP,CHIP 6800PFGHIJK
C	103	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	121	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	123	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	125	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	128	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	403	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	407	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	423	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	453	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	457	87-010-196-080	0E CHIP CAPACITOR,0.1-25FGHIJK
C	102	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	110	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	112	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	114	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	124	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	130	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	131	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	132	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	420	87-010-197-080	0E CAP, CHIP 0.01 DMFGHIJK
C	108	87-010-324-080	0E C-CAP,S 1P-50UJFGHIJK
C	111	87-010-328-080	0E C-CAP,S 5P-50 UJFGHIJK
C	115	87-010-328-080	0E C-CAP,S 5P-50 UJFGHIJK
C	107	87-010-333-080	0E S-CHIP UJ 10PFGHIJK


ELECTRICAL MAIN PARTS LIST - 2

C	117	87-010-334-080	OE	C-CAP,S 12P-50 UJ	FGHIJK.....
C	105	87-010-341-080	OE	C-CAP,S47P-50UJ	FGHIJK.....
C	301	87-010-341-080	OE	C-CAP,S47P-50UJ	FGHIJK.....
C	401	87-010-428-080	OE	C-CAP,S 0.015-25 B	FGHIJK.....
C	451	87-010-428-080	OE	C-CAP,S 0.015-25 B	FGHIJK.....
C	133	87-010-568-080	OE	C-CAP,S 150P-50 UJ	FGHIJK.....
C	101	87-010-570-080	OE	C-CAP,S 220P-50 UJ	FGHIJK.....
C	118	87-010-572-080	OE	C-CAP,S 330P-50 UJ	FGHIJK.....
C	116	87-010-573-080	OE	C-CAP,S 390P-50 UJ	FGHIJK.....
C	104	87-010-574-080	OE	C-CAP,S 470P-50 UJ	FGHIJK.....
C	109	87-010-575-080	OE	C-CAP,S 560P-50 UJ	FGHIJK.....
C	120	87-010-805-080	OE	CAP, S 1-16	FGHIJK.....
C	122	87-010-805-080	OE	CAP, S 1-16	FGHIJK.....
C	304	87-010-805-080	OE	CAP, S 1-16	FGHIJK.....
C	126	87-016-526-080	OE	C-CAP,S 0.47-16 BK	FGHIJK.....
C	402	87-016-526-080	OE	C-CAP,S 0.47-16 BK	FGHIJK.....
C	452	87-016-526-080	OE	C-CAP,S 0.47-16 BK	FGHIJK.....
IC	401	87-017-642-080	1D	IC,CXA1622M	FGHIJK.....
VC	102	87-017-925-070	1A	C-VARI CAP,KV1460	FGHIJK.....
VC	103	87-017-925-070	1A	C-VARI CAP,KV1460	FGHIJK.....
Q	104	87-026-467-080	OE	TR,HN1C01F (0.3W)	FGHIJK.....
IC	101	87-A21-407-040	1E	C-IC,TA2104BFN	FGHIJK.....
VC	101	87-A40-462-040	1B	C-VARI-CAP,SVC347(S)	FGHIJK.....
Q	102	89-115-884-080	OE	CHIP -TRANSISTER 2SA1588Y	FGHIJK.....
Q	301	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	FGHIJK.....
Q	302	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	FGHIJK.....
Q	101	89-342-153-080	OE	TR,2SC4215	FGHIJK.....
Q	103	89-342-153-080	OE	TR,2SC4215	FGHIJK.....
Q	105	89-342-153-080	OE	TR,2SC4215	FGHIJK.....
D	503	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
D	504	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
D	505	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
D	506	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
D	507	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
D	508	87-001-553-080	OE	C-DIODE 1SS322	ABCDE
C	502	87-010-800-080	OE	C-CAP TN 1-10(A2)	ABCDE
C	503	87-010-831-080	OE	C-CAP,U,0.1-16F	ABCDE
C	509	87-010-831-080	OE	C-CAP,U,0.1-16F	ABCDE
C	510	87-010-831-080	OE	C-CAP,U,0.1-16F	ABCDE
C	511	87-010-831-080	OE	C-CAP,U,0.1-16F	ABCDE
C	506	87-012-174-080	OE	CAP CHIP CERA SS 12P CHJ	ABCDE
C	507	87-012-176-080	OE	CAP 15P	ABCDE
C	501	87-012-286-080	OE	CAP, U 0.01-25	ABCDE
C	504	87-016-057-080	1B	C-CAP,TN 47-4/F9.5	ABCDE
C	508	87-016-526-080	OE	C-CAP,S 0.47-16 BK	ABCDE
S	502	87-A90-871-080	1A	C-SW,SL 1-1-2 SSSS810701	ABCDE
S	516	87-A90-871-080	1A	C-SW,SL 1-1-2 SSSS810701	ABCDE
Q	504	89-115-884-080	OE	CHIP -TRANSISTER 2SA1588Y	ABCDE
Q	501	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	ABCDE
Q	503	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	ABCDE
Q	505	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	ABCDE
Q	502	89-508-804-080	1A	CHIP FET 2SK880Y	ABCDE
D	503	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
D	504	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
D	505	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
D	506	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
D	507	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
D	508	87-001-553-080	OE	C-DIODE 1SS322	FGHIJK.....
C	502	87-010-800-080	OE	C-CAP TN 1-10(A2)	FGHIJK.....
C	503	87-010-831-080	OE	C-CAP,U,0.1-16F	FGHIJK.....
C	509	87-010-831-080	OE	C-CAP,U,0.1-16F	FGHIJK.....
C	510	87-010-831-080	OE	C-CAP,U,0.1-16F	FGHIJK.....
C	511	87-010-831-080	OE	C-CAP,U,0.1-16F	FGHIJK.....
C	506	87-012-174-080	OE	CAP CHIP CERA SS 12P CHJ	FGHIJK.....
C	507	87-012-176-080	OE	CAP 15P	FGHIJK.....
C	501	87-012-286-080	OE	CAP, U 0.01-25	FGHIJK.....
C	504	87-016-057-080	1B	C-CAP,TN 47-4/F9.5	FGHIJK.....
C	508	87-016-526-080	OE	C-CAP,S 0.47-16 BK	FGHIJK.....
S	502	87-A90-871-080	1A	C-SW,SL 1-1-2 SSSS810701	FGHIJK.....
S	516	87-A90-871-080	1A	C-SW,SL 1-1-2 SSSS810701	FGHIJK.....
Q	504	89-115-884-080	OE	CHIP -TRANSISTER 2SA1588Y	FGHIJK.....
Q	501	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	FGHIJK.....
Q	503	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	FGHIJK.....
Q	505	89-341-165-080	OE	CHIP TRANSISTOR 2SC4116GR	FGHIJK.....
Q	502	89-508-804-080	1A	CHIP FET 2SK880Y	FGHIJK.....
SP	401	84-TM1-635-010		SP,DIA36	ABCDE
L	104	87-003-152-080	OE	COIL, 100UH	ABCDE
L	401	87-003-383-010	1A	COIL,1UH-S	ABCDE
L	402	87-003-383-010	1A	COIL,1UH-S	ABCDE
L	451	87-003-383-010	1A	COIL,1UH-S	ABCDE
C	406	87-010-097-010		CAP,E 3.3-6.3 K AU	ABCDE
C	456	87-010-097-010		CAP,E 3.3-6.3 K AU	ABCDE
C	127	87-010-098-010		CAP,E 4.7-6.3 K AU	ABCDE
C	421	87-010-420-080	OE	CAP,E 10-6.3 5L	ABCDE
C	422	87-010-420-080	OE	CAP,E 10-6.3 5L	ABCDE
C	129	87-010-482-080	1A	CAP,E 220-4 M 12.5L SRA	ABCDE
C	424	87-010-482-080	1A	CAP,E 220-4 M 12.5L SRA	ABCDE
C	302	87-010-501-080	OE	E/CAP GAS 47-4	ABCDE
C	408	87-010-588-010	OE	ELECT 220-2	ABCDE
C	458	87-010-588-010	OE	ELECT 220-2	ABCDE
D	301	87-020-465-080	OE	DIODE,1SS133 (110MA)	ABCDE
D	302	87-020-465-080	OE	DIODE,1SS133 (110MA)	ABCDE
S	401	87-036-127-010	1A	SLIDE SWITCH	ABCDE

ELECTRICAL MAIN PARTS LIST - 3

J	401	87-A60-760-010	1A	JACK,3.5 ST W/O SW	ABCDE.....
X	501	87-A70-187-010	1B	VIB,XTAL 75KHZ CFV206	ABCDE.....
BPF	101	87-A90-749-010	0E	FLTR,GFMB5	ABCDE.....
CF	102	87-A90-991-010	0E	FLTR,SFE10.7 MS239-A	ABCDE.....
CF	103	87-A91-094-010	1A	FLTR,CDA10.7 MG80A	ABCDE.....
S	101	87-A91-152-010	1A	SW,SL 1-1-2 SSSS212-11-A	ABCDE.....
S	402	87-A91-152-010	1A	SW,SL 1-1-2 SSSS212-11-A	ABCDE.....
CF	101	87-A91-162-010	0E	FLTR,PFS450A7	ABCDE.....
T	101	87-A91-366-010	1A	IFT,MW 5PLG	ABCDE.....
TC	101	87-A91-392-010		TRIMMER,20P	ABCDE.....
S	501	87-A91-732-010		SW,SL 2-2-2 ALZ	ABCDE.....
LED	501	87-A91-734-080		C-LED,PG1113F	ABCDE.....
VR	401	87-A91-735-010		VR,RTRY 50KX1 1 H RK14J11A	ABCDE.....
L	102	8A-RC4-601-010		COIL,FM RF	ABCDE.....
L	103	8A-RC4-602-010		COIL,FM OSC	ABCDE.....
L	101	8A-RC4-603-010		BAR-ANT,MW	ABCDE.....
T	301	8A-RC4-604-010		COIL,D-D CON	ABCDE.....
LCD	101	8A-RC4-607-010		LCD,ARC-4	ABCDE.....
L	104	87-003-152-080	0E	COIL, 100UHFGHIJK.....
L	401	87-003-383-010	1A	COIL,1UH-SFGHIJK.....
L	402	87-003-383-010	1A	COIL,1UH-SFGHIJK.....
L	451	87-003-383-010	1A	COIL,1UH-SFGHIJK.....
C	406	87-010-097-010		CAP,E 3.3-6.3 K AUFGHIJK.....
C	456	87-010-097-010		CAP,E 3.3-6.3 K AUFGHIJK.....
C	127	87-010-098-010		CAP,E 4.7-6.3 K AUFGHIJK.....
C	421	87-010-420-080	0E	CAP,E 10-6.3 5LFGHIJK.....
C	422	87-010-420-080	0E	CAP,E 10-6.3 5LFGHIJK.....
C	129	87-010-482-080	1A	CAP,E 220-4 M 12.5L SRAFGHIJK.....
C	424	87-010-482-080	1A	CAP,E 220-4 M 12.5L SRAFGHIJK.....
C	302	87-010-501-080	0E	E/CAP GAS 47-4FGHIJK.....
C	408	87-010-588-010	0E	ELECT 220-2FGHIJK.....
C	458	87-010-588-010	0E	ELECT 220-2FGHIJK.....
D	301	87-020-465-080	0E	DIODE,1SS133 (110MA)FGHIJK.....
D	302	87-020-465-080	0E	DIODE,1SS133 (110MA)FGHIJK.....
S	401	87-036-127-010	1A	SLIDE SWITCHFGHIJK.....
J	401	87-A60-760-010	1A	JACK,3.5 ST W/O SWFGHIJK.....
X	501	87-A70-187-010	1B	VIB,XTAL 75KHZ CFV206FGHIJK.....
BPF	101	87-A90-749-010	0E	FLTR,GFMB5FGHIJK.....
CF	102	87-A90-991-010	0E	FLTR,SFE10.7 MS239-AFGHIJK.....
CF	103	87-A91-094-010	1A	FLTR,CDA10.7 MG80AFGHIJK.....
S	101	87-A91-152-010	1A	SW,SL 1-1-2 SSSS212-11-AFGHIJK.....
S	402	87-A91-152-010	1A	SW,SL 1-1-2 SSSS212-11-AFGHIJK.....
CF	101	87-A91-162-010	0E	FLTR,PFS450A7FGHIJK.....
T	101	87-A91-366-010	1A	IFT,MW 5PLGFGHIJK.....
TC	101	87-A91-392-010		TRIMMER,20PFGHIJK.....
S	501	87-A91-732-010		SW,SL 2-2-2 ALZFGHIJK.....
LED	501	87-A91-734-080		C-LED,PG1113FFGHIJK.....
VR	401	87-A91-735-010		VR,RTRY 50KX1 1 H RK14J11AFGHIJK.....
L	102	8A-RC4-601-010		COIL,FM RFFGHIJK.....
L	103	8A-RC4-602-010		COIL,FM OSCFGHIJK.....
L	101	8A-RC4-603-010		BAR-ANT,MWFGHIJK.....
T	301	8A-RC4-604-010		COIL,D-D CONFGHIJK.....
LCD	101	8A-RC4-607-010		LCD,ARC-4FGHIJK.....
C	502	87-010-504-080	0E	CAP, CHIP TANTALUM 0.47-25	ABCDE.....
C	504	87-016-436-080	1B	C-CAP,TN 47-4(B2)	ABCDE.....
IC	502	87-A20-755-080	1B	C-IC,AK93C45AF	ABCDE.....
IC	501	87-A21-605-010	1H	C-IC,TC9318FA-056	ABCDE.....
C	502	87-010-504-080	0E	CAP, CHIP TANTALUM 0.47-25FGHIJK.....
C	504	87-016-436-080	1B	C-CAP,TN 47-4(B2)FGHIJK.....
IC	502	87-A20-755-080	1B	C-IC,AK93C45AFFGHIJK.....
IC	501	87-A21-605-010	1H	C-IC,TC9318FA-056FGHIJK.....

SCHEMATIC DIAGRAM-1



MECHANICAL PARTS LIST - 1

NOTE: The characters in the suffix column indicate the part usage.

DS505YH1(S)	XX	B
DS505YJ1(S)	XX	C
DS505YL1(S)	XX	D
D500YU(S)	XX	F
D500YH1(S)	XX	H
D500YJ1(S)	XX	I
D500YL1(S)	XX	J

REF.NO	PARTS NO.	NO.	DESCRIPTION	SUFFIX
	8A-RC4-001-010		CABI, FRONT	ABCDE
	8A-RC4-002-010		CABI, REAR Y	. B. DE
	8A-RC4-003-010		PANEL, FRONT	ABCDE
	8A-RC4-004-010		LID, BATT	ABCDE
	8A-RC4-012-010		WINDOW, LCD	ABCDE
	8A-RC4-013-010		CABI, REAR YZ	A
	8A-RC4-014-010		CABI, REAR YJ	. C
	8A-RC4-004-010		LID, BATT FGHIJK
	8A-RC4-012-010		WINDOW, LCD FGHIJK
	8A-RC5-001-010		CABI, FRONT FGHIJK
	8A-RC5-002-010		PANEL, FRONT FGHIJK
	8A-RC5-006-010		CABI, REAR Y H. JK
	8A-RC5-007-010		CABI, REAR YU F
	8A-RC5-008-010		CABI, REAR YZ G
	8A-RC5-009-010		CABI, REAR YJ I
	8A-RC4-005-010		BTN, PRESET	ABCDE
	8A-RC4-006-010		BTN, BAND/LIGHT	ABCDE
	8A-RC4-007-010		BTN, TUNE/MEMO	ABCDE
	8A-RC4-008-010		KNOB, SL HOLD	ABCDE
	8A-RC4-009-010		KNOB, SL POWER	ABCDE
	8A-RC4-010-010		KNOB, SL MO/ST	ABCDE
	8A-RC4-011-010		KNOB, SL S-BASS	ABCDE
	8A-RC4-005-010		BTN, PRESET FGHIJK
	8A-RC4-008-010		KNOB, SL HOLD FGHIJK
	8A-RC4-009-010		KNOB, SL POWER FGHIJK
	8A-RC4-010-010		KNOB, SL MO/ST FGHIJK
	8A-RC5-003-010		BTN, BAND/LIGHT FGHIJK
	8A-RC5-004-010		BTN, TUNE/MEMO FGHIJK
	8A-RC5-005-010		KNOB, SL S-BASS FGHIJK
	8A-RC4-201-010		LENS, LCD	ABCDE
	8A-RC4-202-010		HLDR, AM ANT	ABCDE
	8A-RC4-203-010		HLDR, JACK	ABCDE
	8A-RC4-204-010		HLDR, PRESET	ABCDE
	8A-RC4-205-010		HLDR, LIGHT/MEMO	ABCDE
	8A-RC4-206-010		COVER, LCD	ABCDE
	8A-RC4-208-010		BAT-CONTACT, (+)	ABCDE
	8A-RC4-209-010		BAT-CONTACT, (-)	ABCDE
	8A-RC4-210-010		BAT-CONTACT, (+-)	ABCDE
	8A-RC4-211-010		CONN, RUBBER LCD	ABCDE
	8A-RC4-201-010		LENS, LCD FGHIJK
	8A-RC4-202-010		HLDR, AM ANT FGHIJK
	8A-RC4-203-010		HLDR, JACK FGHIJK
	8A-RC4-204-010		HLDR, PRESET FGHIJK
	8A-RC4-205-010		HLDR, LIGHT/MEMO FGHIJK
	8A-RC4-206-010		COVER, LCD FGHIJK
	8A-RC4-208-010		BAT-CONTACT, (+) FGHIJK
	8A-RC4-209-010		BAT-CONTACT, (-) FGHIJK
	8A-RC4-210-010		BAT-CONTACT, (+-) FGHIJK
	8A-RC4-211-010		CONN, RUBBER LCD FGHIJK

ACCESSORIES LIST

NOTE: The characters in the suffix column indicate the part usage.

DS505YH1(S)XX.....	B.....
DS505YJ1(S)XX.....	C.....
DS505YL1(S)XX.....	D.....
D500YU(S)XX.....	F.....
D500YH1(S)XX.....	H.....
D500YJ1(S)XX.....	I.....
D500YL1(S)XX.....	J.....

REF.NO	PARTS NO.	NO.	DESCRIPTION	SUFFIX
	8A-RC4-902-010		IB, YHJ(ECC)C	.BC.....
	8A-RC4-904-010		IB, YL(3L)C	...DE.....
	8A-RC4-905-010		IB, YZ(EGF)C	A.....
	8A-RC4-906-010		IB, YZ(SID)C	A.....
	8A-RC4-907-010		IB, YZ(PHNCZ)C	A.....
	8A-RC5-901-010		IB, YU(3L)CF.....
	8A-RC5-902-010		IB, YHJ(ECC)CHI.....
	8A-RC5-904-010		IB, YL(3L)CJK.....
	8A-RC5-905-010		IB, YZ(EGF)CG.....
	8A-RC5-906-010		IB, YZ(SID)CG.....
	8A-RC5-907-010		IB, YZ(PHNCZ)CG.....
	87-B30-240-010	1H	HEADPHONE, HP-M035	ABCDE.....
	87-B30-124-110	1E	HEADPHONE, HP-M028F.....
	87-B30-240-010	1H	HEADPHONE, HP-M035GHIJK.....



アイワ株式会社 〒110-8710 東京都台東区池之端1-2-11 ☎03(3827)3111 (代表)
AIWA CO.,LTD. 2-11, IKENOHATA 1-CHOME, TAITO-KU, TOKYO 110-8710, JAPAN TEL:03 (3827) 3111